

FREEDOM STACK

Portable Power

The Freedom Stack is a portable charging system featuring stackable power banks, each equipped with USB-A/C fast-charging.

Designed with enterprise in mind, Freedom batteries keep you powered up while operating off-site or in collaborative environments without fixed outlets. Upon returning to the stackable charging base they recharge wirelessly, ready for use the next day.



FR001**	1x 78W USB-A/C Power Bank, Unit Only
FR002**	1x Charging Base, Power Supply With 10A 3-Pin Plug
FR003**	1x Charging Base, Power Supply With 10A 3-Pin Plug & 3x 78W USB-A/C Power Banks

Notes:

- ** Denotes Colour: Black (BK), White (WT)

Power Bank

Capacity	18,900mAh (68Wh) +/-5%
Charging Output	USB-C Port PD 60W (5V/3A, 9V/3A, 15V/3A, 20V/3A) USB-A Port QC 3.0/2.0 18W (5V/3A, 9V/2A, 12V/1.5A)
Charging Total	78W (PD60W and QC18W)
Protection	Over-Charge Over-Discharge Over Current Short Circuit Over-Temperature
Charging Input	25W (20V/1.25A) Via Charging Base Only
Size	33.1mm x Ø136.1mm
Weight	0.44kg

Charging Base

Input	100-240Vac
Charging Output	20V/7.5A (150W)
Max Power Banks At Full Charge	5
Charging Time	Around 3.3 Hours
Size	23mm x Ø145mm
Weight	0.36kg
Compliance	CISPR32 AS/NZS CISPR32 EN 55032:2015/A11:2020, EN 55035:2017/AC:2019-11, EN IEC 61000-3-2:2019, EN 61000-3-3:2013/A1:2019 UN38.3

Freedom Batteries are for use with IT/AV Equipment Only

Disclaimer: CMS Electracom has made every attempt to ensure the accuracy and reliability of the information provided in this document are correct. All information contained in this document is to be used for general guidance only. CMS Electracom reserves the right to change, delete or modify the information without notice. V1 2026. For product warranty and returns see cmselectra.com/au/resources/warranty/
© CMS Electracom 2026